

Travel Time and Heat Equation. One space dimensional case II

Masaru IKEHATA

Department of Mathematics, Faculty of Engineering
Gunma University, Kiryu 376-8515, JAPAN

February 2, 2008

Abstract

Three inverse boundary value problems for the heat equations in one space dimension are considered. Those three problems are: extracting an unknown interface in a heat conductive material, an unknown boundary in a layered material or a material with a smooth heat conductivity by employing a single set of the temperature and heat flux on a known boundary as the observation data. Some extraction formulae of those discontinuities which suggest a relationship between the travel time of a *virtual* signal and the observation data are given by applying the enclosure method to the problems.

AMS: 35R30, 80A23

KEY WORDS: heat equation, inverse boundary value problem, reconstruction, heat conduction, inclusion, corrosion, interface, travel time, thermal imaging

1 Introduction

In [11] we considered an inverse boundary value problem for the heat equation in one space dimension. First we recall the problem. Let $a > 0$ and $T > 0$. Let $u = u(x, t)$ be a solution of the problem:

$$\begin{aligned} u_t &= u_{xx} \text{ in }]0, a[\times]0, T[, \\ u_x(a, t) &= 0 \text{ for } t \in]0, T[, \\ u(x, 0) &= 0 \text{ in }]0, a[. \end{aligned} \tag{1.1}$$

Then the problem considered therein is: extract a from a *single set* of the data $u(0, t)$ and $u_x(0, t)$ for $0 < t < T$.

This is a simplest one space dimension version of the problem of domain determination which is a typical inverse boundary value problem for the heat equation and related to the thermal imaging of unknown *discontinuity* such as cavity, defect or inclusion inside a heat conductive body. There are extensive studies for the uniqueness and stability issues of this type of problems in multi dimensions. See [1, 2] and references therein for several results on the issues. However, in our opinion, seeking an analytical formula that

directly connects information about discontinuity with the data also yields another view for understanding of the problems.

Recently, some new analytical methods for the such type inverse problems that the governing equations are elliptic were introduced. In particular, the *probe method* ([5, 10]) and *factorization method* ([14, 15]) gave ways of extracting unknown discontinuity from the data that are given by the Dirichlet-to-Neumann map in inverse boundary value problems; the far field operator or the restriction of the scattered fields onto a sphere surrounding unknown discontinuity that are exerted by infinitely many point sources located on the sphere in inverse obstacle scattering problems.

These methods require infinitely many data. By the way, the *enclosure method* also gives a way of extracting the *convex hull* of unknown discontinuity from the Dirichlet-to-Neumann map ([7]). However in some cases, using the idea of the enclosure method, one can give a way of extracting unknown discontinuity by a single set of the Dirichlet and Neumann data (see [6, 8]). In particular, the result in [8] gave a constructive proof of a uniqueness theorem established in [4] and the numerical implementation of a reconstruction algorithm of the convex hull of unknown polygonal inclusion or cavity has been done in [12, 13]. Thus it is quite interesting whether the enclosure method still works for the inverse problem for the heat equation mentioned above. In [11] we found a simple extraction formula of a by using the idea of the enclosure method. Needless to say, this result gives a new, constructive and simple proof of the uniqueness theorem: the data $u(0, t)$ and $u_x(0, t)$ for $0 < t < T$ uniquely determine a (under a suitable condition on $u_x(0, t)$). However, it should be pointed out that the result in [11] is against the past experiences in the study of inverse boundary value problems for elliptic equations. Here we review the result and point out the difference.

Let c be an arbitrary positive number. Set

$$z = -c\tau \left(1 + i\sqrt{1 - \frac{1}{c^2\tau}} \right), \quad \tau > c^{-2}. \quad (1.2)$$

Let

$$v(x, t) = e^{-z^2 t} e^{xz}. \quad (1.3)$$

Given $s \in \mathbf{R}$ we introduce the *indicator function* $I_c(\tau; s)$:

$$I_c(\tau; s) = e^{\tau s} \int_0^T (-v_x(0, t)u(0, t) + u_x(0, t)v(0, t)) dt, \quad \tau > c^{-2}$$

where u satisfies (1.1) and v is the function given by (1.3).

Assume that we know a positive number M such that $M \geq a$. Let c be an arbitrary positive number satisfying $2Mc < T$. Assume that $u_x(0, t) = 1$ (note that this is just for simplicity of description). Then we have the formula

$$\lim_{\tau \rightarrow \infty} \frac{\log |I_c(\tau; 0)|}{\tau} = -2ca. \quad (1.4)$$

and the following statements are true:

- if $s \leq 2ca$, then $\lim_{\tau \rightarrow \infty} |I_c(\tau; s)| = 0$;
- if $s > 2ca$, then $\lim_{\tau \rightarrow \infty} |I_c(\tau; s)| = \infty$.

Why is this interesting? The reason consists of two points.

The first point is an unexpected asymptotic behaviour of the indicator function. More precisely, integration by parts gives

$$I_c(\tau; s) = -e^{\tau s} \int_0^T u(a, t) v_x(a, t) dt + O(e^{-\tau(T-s)}).$$

The function $e^{\tau s} v$ has the special character

- if $s < cx + t$, then $\lim_{\tau \rightarrow \infty} e^{\tau s} |v(x, t)| = 0$
- if $s > cx + t$, then $\lim_{\tau \rightarrow \infty} e^{\tau s} |v(x, t)| = \infty$.

Therefore if $T > ca > s$, then $|I_c(\tau; s)|$ is exponentially decaying as $\tau \rightarrow \infty$. Since $e^{\tau s} |v_x(a, t)|$ is exponentially growing in the case when $T > s > ca$ and $0 < t < s - ca$, usually we expect $|I_c(\tau; s)|$ is exponentially growing as $\tau \rightarrow \infty$. Then a past experience suggests that the right hand side of (1.4) should give $-ca$ which has the meaning:

$$-ca = \sup \left\{ \begin{pmatrix} x \\ t \end{pmatrix} \cdot \begin{pmatrix} -c \\ -1 \end{pmatrix} \mid (x, t) \in]a, \infty[\times]0, T[\right\}.$$

This is nothing but the value of the support function for the unknown domain $]a, \infty[\times]0, T[$ at the direction $(-c, -1)^T$. However, in fact, we obtained $-2ca$ which has the meaning:

$$-2ca = \sup \left\{ \begin{pmatrix} x \\ t \end{pmatrix} \cdot \begin{pmatrix} -c \\ -1 \end{pmatrix} \mid (x, t) \in]2a, \infty[\times]0, T[\right\}.$$

Since the u of (1.1) can be extended as a solution of the heat equation onto $]a, 2a[$ by the reflection $x \mapsto 2a - x$, one may think that this is because of the simple Neumann boundary condition at $x = a$. However, in [11] we saw the same phenomenon to the case of the Robin boundary condition at $x = a$. So we guess that this is a *universal phenomenon*. Based on this belief, therein we gave another interpretation of $2ca$. It is the *travel time* of a *virtual* signal with an arbitrary fixed propagation speed $1/c$ that starts at the known boundary $x = 0$ and the initial time $t = 0$, reflects at another unknown boundary $x = a$ and returns to the original boundary $x = 0$.

The second point is: needless to say, the formula (1.4) yields a new, simple, constructive proof of the uniqueness theorem.

- Let T be a fixed arbitrary positive number. For $j = 1, 2$ let u_j satisfy (1.1) with $a = a_j (> 0)$ and $(u_j)_x(0, t) = 1$ for all $t \in]0, T[$. If $u_1(0, t) = u_2(0, t)$ for all $t \in]0, T[$, then $a_1 = a_2$.

A standard and traditional proof of this type uniqueness theorem (see, e.g., [1]) is done by using a contradiction argument and starts with assuming, say $a_1 < a_2$. Then the uniqueness of the lateral Cauchy problem for the heat equation gives $u_1(x, t) = u_2(x, t)$ for $(x, t) \in]0, a_1[\times]0, T[$. This yields that u_2 satisfies $(u_2)_x(a_1, t) = (u_1)_x(a_1, t) = 0$. Since u_2 satisfies the heat equation in $]a_1, a_2[\times]0, T[$, the Neumann boundary conditions at $x = a_1, a_2$ and the initial condition $u_2(x, 0) = 0$, we obtain $u_2(x, t) = 0$ in $]a_1, a_2[\times]0, T[$. Then the unique continuation theorem for the solution of the heat equation gives $u_2(x, t) = 0$ in $]0, a_2[\times]0, T[$ and this thus yields $(u_2)_x(0, t) = 0$. Contradiction.

Clearly this argument can relax the condition on $u_x(0, t)$ and tells us the importance of the uniqueness of the lateral Cauchy problem or the unique continuation theorem for the heat equation. However, this type proof gives no information about how to extract unknown a from the data $u(0, t)$ and $u_x(0, t)$.

It should be pointed out that, in [1] another argument in the case when $T = \infty$ and one has the data $u(0, t)$ and $u_x(0, t)$ for all $t \in]0, \infty[$, is introduced. Starting with assuming $a_1 < a_2$, we see that u_2 satisfies the Neumann boundary conditions at $x = a_1, a_2$. This is same as above. However, here they do not make use of the initial condition $u_2(x, 0) = 0$. Instead they have the identity

$$\frac{d}{dt} \int_{a_1}^{a_2} u_2(x, t) dt = \int_{a_1}^{a_2} (u_2)_{xx}(x, t) dt = 0.$$

One the other hand, using the eigenfunction expansion, they show that

$$\lim_{t \rightarrow \infty} \left| \int_{a_1}^{a_2} u_2(x, t) dt \right| = \infty.$$

Contradiction. The proof is quite interesting, however, clearly in this argument the assumption $T = \infty$ is essential and the same comment works also for this proof.

Summing up, one should find another type proof that tells us the information about how to extract unknown a from the data $u(0, t)$ and $u_x(0, t)$ for $t \in]0, T[$ with $T < \infty$. We think that our proof presented in this paper gives an answer to this natural question.

The aim of this paper is: to confirm further that the interpretation in the first point still works, at least, in one space dimensional case by considering three typical inverse boundary value problems for the heat equations. Those three problems are: extracting an unknown interface in a conductive material, an unknown boundary in a layered material or a material with a smooth conductivity.

In a future study we will consider the multidimensional version of those problems.

Remark 1.1. In this paper we always consider the solutions of the heat equations in the context of a variational formulation. In particular, every solutions in this paper belongs to the space $W(0, T; H^1(\Omega), (H^1(\Omega))')$ with $u_x(0, t), u_x(a, t) \in L^2(0, T)$ where $\Omega =]0, a[$ and satisfies the governing equation in a weak sense. We refer the reader to [3] for the detail.

2 Statement of the results

2.1. Extracting interface

Let $0 < b < a$. Define

$$\gamma(x) = \begin{cases} \gamma_1, & \text{if } 0 < x < b, \\ \gamma_2, & \text{if } b < x < a \end{cases}$$

where both γ_1 and γ_2 are positive constants and satisfies $\gamma_2 \neq \gamma_1$.

Let u be an arbitrary solution of the problem:

$$\begin{aligned} u_t &= (\gamma u_x)_x \text{ in }]0, a[\times]0, T[, \\ u(x, 0) &= 0 \text{ in }]0, a[. \end{aligned} \tag{2.1}$$

We assume that both γ_1 is *known* and that a, b and γ_2 are all *unknown*.

Inverse Problem A. Extract b from $u(0, t)$ and $\gamma_1 u_x(0, t)$ for $0 < t < T$.

Let c be an arbitrary positive number. Let

$$v(x, t) = e^{-z^2 t} \Psi(x, z) \quad (2.2)$$

where $\Psi(x, z) = e^{x z_1}$, $z_1 = z/\sqrt{\gamma_1}$ and z is given by (1.2).

The function v is a complex valued function and satisfies the backward heat equation $v_t + \gamma_1 v_{xx} = 0$ in the whole space-time.

Definition 2.1. Given $c > 0$ define the *indicator function* $I_c(\tau)$ by the formula

$$I_c(\tau) = \int_0^T (-\gamma_1 v_x(0, t)u(0, t) + \gamma_1 u_x(0, t)v(0, t)) dt, \quad \tau > c^{-2}$$

where u satisfies (2.1) and v is the function given by (2.2).

Define

$$w(x) = w(x, \tau) = \int_0^T e^{-z^2 t} u(x, t) dt, \quad 0 < x < a.$$

Then this w satisfies

$$(\gamma w')' - z^2 w = e^{-z^2 T} u(x, T) \text{ in }]0, a[\quad (2.3)$$

and

$$w'(0) = \int_0^T e^{-z^2 t} u_x(0, t) dt, \quad w'(a) = \int_0^T e^{-z^2 t} u_x(a, t) dt.$$

Our first result is the following theorem:

Theorem 2.1. Assume that we know a positive number M such that $M \geq 2b/\sqrt{\gamma_1}$. Let c be an arbitrary positive number satisfying $Mc < T$. Assume that

$$\lim_{\tau \rightarrow \infty} \left| \frac{w'(a)}{w'(0)} \right| \exp \left(c \tau \left(\frac{b}{\sqrt{\gamma_1}} - \frac{(a-b)}{\sqrt{\gamma_2}} \right) \right) = 0 \quad (2.4)$$

and there exist a positive constant C , positive number τ_0 , real number μ such that, for all $\tau > \tau_0$

$$C \tau^\mu \leq |w'(0)|. \quad (2.5)$$

Then the formula

$$\lim_{\tau \rightarrow \infty} \frac{\log |I_c(\tau)|}{\tau} = -2 \frac{cb}{\sqrt{\gamma_1}},$$

is valid.

Note that the boundary condition at $x = a$ is not specified. However, the condition (2.4) implicitly restricts a possible boundary condition at $x = a$. The situation dramatically changes in the case when (a) $b/\sqrt{\gamma_1} < (a-b)/\sqrt{\gamma_2}$ or (b) $b/\sqrt{\gamma_1} > (a-b)/\sqrt{\gamma_2}$.

In case (a) the condition (2.5) automatically ensures that (2.4) is valid since we have always $w'(a) = O(1)$ as $\tau \rightarrow \infty$ (Remark 1.1). This is reasonable under our interpretation since the signal started from $x = a$ at $t = 0$ arrives at $x = 0$ after the arrival of the signal started at $x = 0$ at $t = 0$ (see Figure 1).

However in case (b) to ensure (2.4) $w'(a)$ has to decay exponentially as $\tau \rightarrow \infty$. This is a strong restriction and can be interpreted as a condition that kills a signal started from $x = a$ at $t = 0$ (see Figure 2).




Figure 1: (a) $b/\sqrt{\gamma_1} < (a-b)/\sqrt{\gamma_2}$.




Figure 2: (b) $b/\sqrt{\gamma_1} > (a-b)/\sqrt{\gamma_2}$.

The condition (2.5) gives a restriction on the behaviour of the flux $u_x(0, t)$ as $t \downarrow 0$. Let δ satisfy $0 < \delta < T$ and $m \geq 0$ be an integer. Since

$$z^2 = \tau + i2c^2\tau^2\sqrt{1 - \frac{1}{c^2\tau}},$$

a change of variable yields, as $\tau \rightarrow \infty$

$$\begin{aligned} \int_0^\delta e^{-z^2 t} t^m dt &= \frac{1}{\tau^{m+1}} \int_0^{\tau\delta} e^{-\xi(1 + i2c^2\tau\sqrt{1 - \frac{1}{c^2\tau}})} \xi^m d\xi \\ &= \frac{1}{\tau^{m+1}} \int_0^\infty e^{-c^2\tau(1 + i\sqrt{1 - \frac{1}{c^2\tau}})^2\xi} \xi^m d\xi + O(\tau^{-\infty}) \\ &= \frac{1}{\tau^{2(m+1)}} \int_0^\infty e^{-c^2(1 + i\sqrt{1 - \frac{1}{c^2\tau}})^2 t} t^m dt + O(\tau^{-\infty}). \end{aligned}$$

Integration by parts gives

$$\int_0^\infty e^{-c^2(1 + i\sqrt{1 - \frac{1}{c^2\tau}})^2 t} t^m dt = m! K(\tau)^{m+1}$$

where

$$K(\tau) = \frac{1}{c^2(1 + i\sqrt{1 - \frac{1}{c^2\tau}})^2} \rightarrow \frac{-i}{2c^2}.$$

Therefore we obtain, as $\tau \rightarrow \infty$

$$\tau^{2(m+1)} \int_0^\delta e^{-z^2 t} t^m dt \rightarrow m! \left(-\frac{i}{2c^2}\right)^{m+1} \neq 0.$$

It is easy to see that if $f \in L^2(0, T)$ and for a suitable positive constant C , $|f(t)| \leq Ct^{m'}$ a. e. in $]0, \delta[$, then, as $\tau \rightarrow \infty$

$$\int_0^T e^{-z^2 t} f(t) dt = O(\tau^{-(m'+1)}).$$

Now assume that, we have, for some δ , a positive constant C

$$|u_x(0, t) - (g_l t^l + g_{l+1} t^{l+1} + \dots + g_n t^n)| \leq Ct^{m'+1}, \text{ a. e. in }]0, \delta[$$

where n, l and m' are integers and satisfy $n \geq l \geq 0$ and $m' > 2l + 1$; $g_l, \dots, g_n$ are constants and satisfy $g_l \neq 0$. Then from the computation above we see that, as $\tau \rightarrow \infty$

$$\tau^{2(l+1)} \int_0^T e^{-z^2 t} u_x(0, t) dt \rightarrow g_l l! \left(-\frac{i}{2c^2}\right)^{l+1}.$$

This implies that $u_x(0, t)$ satisfies (2.5). In particular, the condition (2.5) is satisfied if $u_x(0, t)$ satisfies one of the following conditions

- $u_x(0, t) \in C^2([0, \delta])$ and $u_x(0, 0) \neq 0$
- $u_x(0, t) \in C^{2l+2}([0, \delta])$ with $l \geq 1$ and $t = 0$ is the zero point of $u_x(0, t)$ with order l .

2.2. Extracting unknown boundary. Layered material

Let $0 = b_0 < b_1 < b_2 < \dots < b_m = a$.

$$\gamma(x) = \begin{cases} \gamma_1, & \text{if } b_0 < x < b_1, \\ \gamma_2, & \text{if } b_1 < x < b_2, \\ \vdots & \\ \gamma_m, & \text{if } b_{m-1} < x < b_m \end{cases}$$

where $\gamma_1, \gamma_2, \dots, \gamma_m$ are positive constants and $m \geq 1$.

Let $a > 0$. Let $u = u(x, t)$ be an arbitrary solution of the problem:

$$\begin{aligned} u_t &= (\gamma u_x)_x \text{ in }]0, a[\times]0, T[, \\ \gamma_m u_x(a, t) + \rho u(a, t) &= 0 \text{ for } t \in]0, T[, \\ u(x, 0) &= 0 \text{ in }]0, a[\end{aligned} \tag{2.6}$$

here $\rho \geq 0$ is an arbitrary fixed constant.

Inverse Problem B. Assume that $\gamma_1, \dots, \gamma_m$ are *known* and that both of ρ and a are *unknown*. Extract a from $u(0, t)$ and $\gamma_1 u_x(0, t)$ for $0 < t < T$.

In this subsection, instead of Ψ in the previous subsection the function Ψ in the following which is a consequence of Lemma 5.1 in Section 5 plays the same role; z is given by (1.2) and set $z_j = z/\sqrt{\gamma_j}$, $j = 1, \dots, m$.

Proposition 2.2. *There exists a positive number $C = C(c, \gamma_1, \dots, \gamma_m) (> c^{-2})$ such that: for each $\tau > C$ there exist a unique $U = (B_1, A_2, B_2, \dots, A_{m-1}, B_{m-1}, A_m)$ such that the function Ψ defined by the formula*

$$\Psi(x) = \Psi(x; c, \gamma_1, \dots, \gamma_m, \tau) = \begin{cases} e^{xz_1} + B_1 e^{-xz_1}, & \text{if } x < b_1, \\ A_2 e^{xz_2} + B_2 e^{-xz_2}, & \text{if } b_1 < x < b_2, \\ \vdots & \\ A_{m-1} e^{xz_{m-1}} + B_{m-1} e^{-xz_{m-1}}, & \text{if } b_{m-2} < x < b_{m-1}, \\ A_m e^{xz_m}, & \text{if } b_{m-1} < x \end{cases}$$

satisfies the equation

$$(\tilde{\gamma} \Psi)' - z^2 \Psi = 0 \text{ in } \mathbf{R}$$

where

$$\tilde{\gamma}(x) = \begin{cases} \gamma_1, & \text{if } -\infty < x < b_1, \\ \gamma_2, & \text{if } b_1 < x < b_2, \\ \vdots & \\ \gamma_m, & \text{if } b_{m-1} < x < \infty. \end{cases}$$

Using Ψ in Proposition 2.2, we define the special solution of the backward heat equation $v_t + (\gamma v_x)_x = 0$ in $\mathbf{R}$ by the formula

$$v(x, t) = e^{-z^2 t} \Psi(x; c, \gamma_1, \dots, \gamma_m, \tau), \quad \tau > C(c; \gamma_1, \dots, \gamma_m)$$

Now we can define the indicator function.

Definition 2.2. Given $c > 0$ define the *indicator function* $I_c(\tau)$ by the formula

$$I_c(\tau) = \int_0^T (-\gamma_1 v_x(0, t)u(0, t) + \gamma_1 u_x(0, t)v(0, t)) dt, \quad \tau > C(c; \gamma_1, \dots, \gamma_m)$$

where u satisfies (2.6).

The following gives a solution to the problem mentioned above and generalizes Theorem 4.1 of [11].

Theorem 2.3. Assume that we know a positive number M such that

$$M \geq 2 \left(\frac{b_1}{\sqrt{\gamma_1}} + \sum_{j=1}^{m-1} \frac{(b_{j+1} - b_j)}{\sqrt{\gamma_{j+1}}} \right).$$

Let c be an arbitrary positive number satisfying $Mc < T$. Assume that there exist positive a constant C , positive number $\tau_0 (> c^{-2})$, real number μ such that, for all $\tau > \tau_0$

$$C \tau^\mu \leq \left| \int_0^T e^{-z^2 t} u_x(0, t) dt \right|. \quad (2.7)$$

Then the formula

$$\lim_{\tau \rightarrow \infty} \frac{\log |I_c(\tau)|}{\tau} = -2c \left(\frac{b_1}{\sqrt{\gamma_1}} + \sum_{j=1}^{m-1} \frac{(b_{j+1} - b_j)}{\sqrt{\gamma_{j+1}}} \right), \quad (2.8)$$

is valid.

Needless to say, the quantity

$$2c \left(\frac{b_1}{\sqrt{\gamma_1}} + \sum_{j=1}^{m-1} \frac{(b_{j+1} - b_j)}{\sqrt{\gamma_{j+1}}} \right)$$

can be interpreted as the travel time of a virtual signal with propagation speeds $\sqrt{\gamma_1}/c, \sqrt{\gamma_2}/c, \dots, \sqrt{\gamma_m}/c$ in the layers $0 < x < b_1, b_1 < x < b_2, \dots, b_{m-1} < x < a$,

respectively that starts at the known boundary $x = 0$ and the initial time $t = 0$, reflects at another unknown boundary $x = a$ and returns to the original boundary $x = 0$.

2.3. Extracting unknown boundary. Material with smooth conductivity

Let $a > 0$. Let $M \geq a$. Let $\gamma \in C^2([0, M])$ and satisfy $\gamma(x) > 0$ for all $x \in [0, M]$. Let $u = u(x, t)$ be an arbitrary solution of the problem:

$$\begin{aligned} u_t &= (\gamma u_x)_x \text{ in }]0, a[\times]0, T[, \\ \gamma(a) u_x(a, t) + \rho u(a, t) &= 0 \text{ for } t \in]0, T[, \\ u(x, 0) &= 0 \text{ in }]0, a[\end{aligned} \tag{2.9}$$

here $\rho \geq 0$ is an arbitrary fixed constant.

Inverse Problem C. Assume that both M and γ are *known* and that both of ρ and a are *unknown*. Extract a from $u(0, t)$ and $\gamma(0) u_x(0, t)$ for $0 < t < T$.

We start with a fact which can be deduced from a combination of Theorem 1 of p. 48 in [16] and the Liouville transform.

Proposition 2.4. *Given z with $\operatorname{Re} z \leq 0$ there exists a solution $\Psi = \Psi(\cdot; z, M)$ of the equation $(\gamma y')' - z^2 y = 0$, $0 < x < M$ such that, as $|z| \rightarrow \infty$*

$$\begin{aligned} \Psi(x; z, M) &= \{\gamma(x)\}^{-1/4} \exp \left(z \int_0^x \frac{dx}{\sqrt{\gamma(x)}} \right) \left\{ 1 + O \left(\frac{1}{|z|} \right) \right\}, \\ \Psi'(x; z, M) &= z \{\gamma(x)\}^{-3/4} \exp \left(z \int_0^x \frac{dx}{\sqrt{\gamma(x)}} \right) \left\{ 1 + O \left(\frac{1}{|z|} \right) \right\} \end{aligned}$$

uniformly in $x \in [0, M]$.

Using Ψ in Proposition 2.4, we define the special solution of the backward heat equation $v_t + (\gamma v_x)_x = 0$ in $]0, M[\times]0, T[$ by the formula

$$v(x, t) = e^{-z^2 t} \Psi(x; z, M).$$

Now we can define the indicator function.

Definition 2.3. Define the *indicator function* $I(z)$ by the formula

$$I(z) = \int_0^T (-\gamma(0) v_x(0, t) u(0, t) + \gamma(0) u_x(0, t) v(0, t)) dt, \quad \operatorname{Re} z \leq 0$$

where u satisfies (2.9).

The following gives two solutions to the problem mentioned above and generalizes Theorem 4.1 of [11].

Theorem 2.5. *Assume that we know a positive number M such that $M \geq a$.*

(1) *Let c be an arbitrary positive number satisfying*

$$T > 2c \int_0^M \frac{dx}{\sqrt{\gamma(x)}}. \tag{2.10}$$

Let z be the number given by (1.2). Assume that there exist positive constant C and a positive number $\tau_0(> c^{-2})$, real number μ such that, for all $\tau > \tau_0$

$$C \tau^\mu \leq \left| \int_0^T e^{-z^2 t} u_x(0, t) dt \right|. \quad (2.11)$$

Then the formula

$$\lim_{\tau \rightarrow \infty} \frac{\log |I(z)|}{\tau} = -2c \int_0^a \frac{dx}{\sqrt{\gamma(x)}}, \quad (2.12)$$

is valid.

(2) Assume that there exist positive constant C and a positive number τ_0 , real number μ such that, for all $\tau > \tau_0$

$$C \tau^\mu \leq \left| \int_0^T e^{-\tau^2 t} u_x(0, t) dt \right|. \quad (2.13)$$

Then the formula

$$\lim_{\tau \rightarrow \infty} \frac{\log |I(-\tau)|}{\tau} = -2 \int_0^a \frac{dx}{\sqrt{\gamma(x)}}, \quad (2.14)$$

is valid.

The quantity

$$2c \int_0^a \frac{dx}{\sqrt{\gamma(x)}}$$

coincides with the travel time of a virtual signal with variable propagation speed $\sqrt{\gamma(x)}/c$ that starts at the known boundary $x = 0$ and the initial time $t = 0$, reflects at another unknown boundary $x = a$ and returns to the original boundary $x = 0$.

The condition (2.13) is less restrictive compared with condition (2.11). We can easily see that the condition (2.13) is satisfied if $u_x(0, t)$ satisfies one of the following conditions

- for a positive constant C $u_x(0, t) \geq C$ a.e. in $]0, \delta[$
- $u_x(0, t) \in C^1([0, \delta])$ and $u_x(0, 0) \neq 0$
- $u_x(0, t) \in C^{l+1}([0, \delta])$ with $l \geq 1$ and $t = 0$ is the zero point of $u_x(0, t)$ with order l .

See the end of subsection 2.1 for the comparison.

As a corollary of Theorem 2.5 we obtain a direct proof of *uniqueness theorem*: the data $u(0, t)$ and $u_x(0, t)$ for $0 < t < T$ uniquely determine a provided one of (2.11) for a c satisfying (2.10) or (2.13) is satisfied and both M and γ are known. Note that T is an arbitrary fixed positive number. In the proof we never make use of the uniqueness of the lateral Cauchy problem nor the unique continuation theorem for the heat equation with a variable coefficient.

3 Proof of Theorem 2.1

Since Ψ satisfies $\gamma_1 \Psi'' - z^2 \Psi = 0$ in $\mathbf{R}$, integration by parts gives the expression of the indicator function:

$$\begin{aligned} I_c(\tau) = & -\gamma_1 \Psi'(a)w(a) + \gamma_2 w'(a)\Psi(a) + (\gamma_1 - \gamma_2) \int_b^a w'(x)\Psi'(x)dx \\ & - e^{-z^2 T} \int_0^a u(\xi, T)\Psi(\xi)d\xi. \end{aligned} \quad (3.1)$$

Let y be the solution of the boundary value problem

$$(\gamma y')' - z^2 y = 0 \text{ in }]0, a[,$$

$$y'(0) = w'(0), \quad y'(a) = w'(a).$$

Define the *principle part* of the indicator function

$$I_c^0(\tau) = -\gamma_1 \Psi'(a) y(a) + \gamma_2 y'(a) \Psi(a) + (\gamma_1 - \gamma_2) \int_b^a y'(x) \Psi'(x) dx. \quad (3.2)$$

It is easy to see that Theorem 2.1 is a direct consequence of the following two lemmas

Lemma 3.1. *Assume that $w'(a)$ and $w'(0)$ satisfy (2.4) and (2.5). Then, choosing suitable positive constants C'_1 and C'_2 and positive number τ'_0 , we have*

$$C'_1 \tau^\mu \leq |I_c^0(\tau)| e^{2c\tau b/\sqrt{\gamma_1}} \leq C'_2, \quad \forall \tau > \tau'_0.$$

Lemma 3.2. *As $\tau \rightarrow \infty$*

$$I_c(\tau) = I_c^0(\tau) + O(e^{-\tau T}).$$

First we prove Lemma 3.1. The y has the expression

$$y(x) = y(x, \tau) = \begin{cases} A_1 e^{x z_1} + B_1 e^{-x z_1}, & \text{if } 0 < x < b, \\ A_2 e^{x z_2} + B_2 e^{-x z_2}, & \text{if } b < x < a \end{cases}$$

and has to satisfy the transmission conditions:

$$y(b-0) = y(b+0), \quad \gamma_1 y'(b-0) = \gamma_2 y'(b+0).$$

These and the relation $z_2/z_1 = \sqrt{\gamma_1/\gamma_2}$ yield the system of equations:

$$A_1 e^{b z_1} + B_1 e^{-b z_1} = A_2 e^{b z_2} + B_2 e^{-b z_2}; \quad (3.3)$$

$$A_1 e^{b z_1} - B_1 e^{-b z_1} = \sqrt{\frac{\gamma_2}{\gamma_1}} (A_2 e^{b z_2} - B_2 e^{-b z_2}). \quad (3.4)$$

Moreover the boundary conditions $y'(0) = w'(0)$ and $y'(a) = w'(a)$ yield

$$z_1 (A_1 - B_1) = w'(0) \quad (3.5)$$

and

$$z_2 (A_2 e^{a z_2} - B_2 e^{-a z_2}) = w'(a). \quad (3.6)$$

A combination of (3.3) and (3.4) gives

$$\begin{aligned} A_1 e^{b z_1} &= \frac{1}{2} \left(1 + \sqrt{\frac{\gamma_2}{\gamma_1}} \right) A_2 e^{b z_2} + \frac{1}{2} \left(1 - \sqrt{\frac{\gamma_2}{\gamma_1}} \right) B_2 e^{-b z_2}, \\ B_1 e^{-b z_1} &= \frac{1}{2} \left(1 - \sqrt{\frac{\gamma_2}{\gamma_1}} \right) A_2 e^{b z_2} + \frac{1}{2} \left(1 + \sqrt{\frac{\gamma_2}{\gamma_1}} \right) B_2 e^{-b z_2}. \end{aligned} \quad (3.7)$$

Define

$$T_{kl} = \frac{2\sqrt{\gamma_k}}{\sqrt{\gamma_k} + \sqrt{\gamma_l}}, \quad R_{kl} = \frac{\sqrt{\gamma_k} - \sqrt{\gamma_l}}{\sqrt{\gamma_k} + \sqrt{\gamma_l}}.$$

We have

$$\frac{1}{2} \left(1 + \sqrt{\frac{\gamma_2}{\gamma_1}} \right) = \frac{1}{T_{12}}, \quad \frac{1}{2} \left(1 - \sqrt{\frac{\gamma_2}{\gamma_1}} \right) = \frac{R_{12}}{T_{12}}.$$

Then (3.7) becomes equations

$$A_1 e^{bz_1} = \frac{1}{T_{12}} A_2 e^{bz_2} + \frac{R_{12}}{T_{12}} B_2 e^{-bz_2}, \quad (3.8)$$

$$B_1 e^{-bz_1} = \frac{R_{12}}{T_{12}} A_2 e^{bz_2} + \frac{1}{T_{12}} B_2 e^{-bz_2}. \quad (3.9)$$

Substituting (3.8) and (3.9) into (3.5) and (3.6), we obtain

$$R \begin{pmatrix} A_2 e^{bz_2} \\ B_2 e^{-bz_2} \end{pmatrix} = \frac{1}{z} \begin{pmatrix} \sqrt{\gamma_2} w'(a) \\ \sqrt{\gamma_1} w'(0) e^{bz_1} \end{pmatrix} \quad (3.10)$$

where

$$R = \begin{pmatrix} e^{(a-b)z_2} & -e^{-(a-b)z_2} \\ \begin{pmatrix} 1 & -e^{2bz_1} \end{pmatrix} \begin{pmatrix} \frac{1}{T_{12}} & \frac{R_{12}}{T_{12}} \\ \frac{R_{12}}{T_{12}} & \frac{1}{T_{12}} \end{pmatrix} \end{pmatrix} = \begin{pmatrix} e^{(a-b)z_2} & -e^{-(a-b)z_2} \\ \frac{1}{T_{12}} (1 - R_{12} e^{2bz_1}) & \frac{1}{T_{12}} (R_{12} - e^{2bz_1}) \end{pmatrix}.$$

A direct computation gives

$$(\det R) T_{12} e^{(a-b)z_2} = 1 + R_{12} (e^{2(a-b)z_2} - e^{2bz_1}) - e^{2bz_1+2(a-b)z_2}.$$

This yields, as $\tau \longrightarrow \infty$

$$(\det R) T_{12} e^{(a-b)z_2} = 1 + O \left(e^{-2c\tau \min(b/\sqrt{\gamma_1}, (a-b)/\sqrt{\gamma_2})} \right). \quad (3.11)$$

Therefore R is invertible for sufficiently large τ . It follows from (3.10) that A_2, B_2 have the form

$$A_2 = \frac{e^{-bz_2}}{z(\det R)} \left(\frac{1}{T_{12}} (R_{12} - e^{2bz_1}) \sqrt{\gamma_2} w'(a) + e^{-(a-b)z_2} \sqrt{\gamma_1} w'(0) e^{bz_1} \right), \quad (3.12)$$

$$B_2 = \frac{e^{bz_2}}{z(\det R)} \left(\frac{1}{T_{12}} (R_{12} e^{2bz_1} - 1) \sqrt{\gamma_2} w'(a) + e^{(a-b)z_2} \sqrt{\gamma_1} w'(0) e^{bz_1} \right). \quad (3.13)$$

Using (3.12) and (3.13), we get two crucial formulae:

$$(\gamma_1 - \gamma_2) \int_b^a y'(x) \Psi'(x) dx = \frac{1}{(\det R) T_{12}} (C \sqrt{\gamma_2} w'(a) + D T_{12} \sqrt{\gamma_1} w'(0))$$

where

$$\begin{aligned} C &= (\sqrt{\gamma_1} - \sqrt{\gamma_2})(R_{12} - e^{2b z_1})(e^{a z_1 + (a-b) z_2} - e^{b z_1}) \\ &\quad + (\sqrt{\gamma_1} + \sqrt{\gamma_2})(R_{12} e^{2b z_1} - 1)(e^{a z_1 - (a-b) z_2} - e^{b z_1}), \\ D &= 2\sqrt{\gamma_1} e^{(a+b) z_1} \\ &\quad - (\sqrt{\gamma_1} - \sqrt{\gamma_2}) e^{2b z_1 - (a-b) z_2} - (\sqrt{\gamma_1} + \sqrt{\gamma_2}) e^{2b z_1 + (a-b) z_2}; \\ -\gamma_1 \Psi'(a) y(a) + \gamma_2 y'(a) \Psi(a) &= \frac{1}{(\det R) T_{12}} (\tilde{C} \sqrt{\gamma_2} w'(a) + \tilde{D} T_{12} \sqrt{\gamma_1} w'(0)) \end{aligned}$$

where

$$\begin{aligned} \tilde{C} &= -(\sqrt{\gamma_1} - \sqrt{\gamma_2})(R_{12} - e^{2b z_1}) e^{a z_1 + (a-b) z_2} \\ &\quad - (\sqrt{\gamma_1} + \sqrt{\gamma_2})(R_{12} e^{2b z_1} - 1) e^{a z_1 - (a-b) z_2}, \\ \tilde{D} &= -2\sqrt{\gamma_1} e^{(a+b) z_1}. \end{aligned}$$

A combination of those and (3.2) gives the representation formula

$$\begin{aligned} (\det R) T_{12} I_c^0(\tau) &= -2 \sqrt{\gamma_1} \sqrt{\gamma_2} w'(a) e^{b z_1} \\ &\quad - \left((\sqrt{\gamma_1} - \sqrt{\gamma_2}) e^{2b z_1 - (a-b) z_2} + (\sqrt{\gamma_1} + \sqrt{\gamma_2}) e^{2b z_1 + (a-b) z_2} \right) T_{12} \sqrt{\gamma_1} w'(0). \end{aligned} \tag{3.14}$$

Note that

$$\begin{aligned} &(\sqrt{\gamma_1} - \sqrt{\gamma_2}) e^{2b z_1 - (a-b) z_2} + (\sqrt{\gamma_1} + \sqrt{\gamma_2}) e^{2b z_1 + (a-b) z_2} \\ &= e^{2b z_1 - (a-b) z_2} (\sqrt{\gamma_1} - \sqrt{\gamma_2}) \left(1 + O(e^{-2c\tau(a-b)/\sqrt{\gamma_2}}) \right). \end{aligned}$$

Note also that Remark 1.1 gives $w'(0) = O(1)$ as $\tau \rightarrow \infty$. Using these, (3.11), (3.14), (2.4), (2.5) and the assumption $\gamma_1 \neq \gamma_2$, we get the assertion of Lemma 3.1.

□

Next we give a proof of Lemma 3.2. Recalling (3.1) and (3.2), we get

$$\begin{aligned} I_c(\tau) - I_c^0(\tau) &= -\gamma_1 \Psi'(a) \epsilon(a) + (\gamma_1 - \gamma_2) \int_b^a \epsilon'(x) \Psi'(x) dx - e^{-z^2 T} \int_0^a u(\xi, T) \Psi(\xi) d\xi \end{aligned} \tag{3.15}$$

where $\epsilon(y) = w(y) - y(x)$. One knows

$$\int_0^a u(\xi, T) \Psi(\xi) d\xi = O(1). \tag{3.16}$$

The ϵ satisfies

$$(\gamma \epsilon')' - z^2 \epsilon = e^{-z^2 T} u(x, T) \text{ in }]0, a[,$$

$$\epsilon'(0) = \epsilon'(a) = 0.$$

Multiplying the both sides of the equation by $\bar{\epsilon}$ and integrating the resultant over interval $]0, a[$, we have

$$\int_0^a \gamma |\epsilon'|^2 dx + z^2 \int_0^a |\epsilon|^2 dx = -e^{-z^2 T} \int_0^a u(\xi, T) \bar{\epsilon}(\xi) d\xi.$$

Since

$$z^2 = \tau + i2c^2\tau^2 \sqrt{1 - \frac{1}{c^2\tau}},$$

a standard argument yields, as $\tau \longrightarrow \infty$

$$\|\epsilon\|_{H^1([0, a])} = O(e^{-\tau T}).$$

A combination of this and the embedding $H^1([0, a]) \subset C^0([0, a])$ gives the estimates

$$\begin{aligned} -\gamma_1 \Psi'(a) \epsilon(a) &= O\left(\tau \exp\left(-\tau\left(T + \frac{ca}{\sqrt{\gamma_1}}\right)\right)\right), \\ \int_b^a \epsilon'(x) \Psi'(x) dx &= O\left(\tau \exp\left(-\tau\left(T + \frac{cb}{\sqrt{\gamma_1}}\right)\right)\right). \end{aligned} \tag{3.17}$$

Now we obtain from (3.15), (3.16) and (3.17) the assertion of Lemma 3.2.

□

4 Proof of Theorem 2.3. Part 1. Asymptotic behaviour of $w(a)$

Define

$$w(x) = w(x, \tau) = \int_0^T u(x, t) e^{-z^2 t} dt, \quad 0 < x < a.$$

This $w(x)$ satisfies

$$(\gamma w')' - z^2 w = e^{-z^2 T} u(x, T) \text{ in }]0, a[,$$

$$\gamma_m w'(a) + \rho w(a) = 0.$$

In this section we study the asymptotic behaviour of $w(a)$ as $\tau \longrightarrow \infty$. For the purpose it suffices to study the asymptotic behaviour of the solution of the boundary value problem as $\tau \longrightarrow \infty$:

$$(\gamma y')' - z^2 y = 0 \text{ in }]0, a[,$$

$$y'(0) = w'(0),$$

$$\gamma_m y'(a) + \rho y(a) = 0.$$

This is because of

Lemma 4.1. *Let $\rho \geq 0$. The formula*

$$w(a) = y(a) + O(e^{-\tau T}),$$

is valid.

Proof. Define

$$\epsilon(x) = w(x) - y(x), \quad 0 < x < a.$$

This function satisfies

$$(\gamma \epsilon')' - z^2 \epsilon = e^{-z^2 T} u(x, T) \text{ in }]0, a[,$$

$$\epsilon'(0) = 0,$$

$$\gamma_m \epsilon'(a) + \rho \epsilon(a) = 0.$$

Hereafter a combination of a standard argument and the embedding $H^1(]0, a[) \subset C^0([0, a])$ yields the desired estimate.

□

For each $j = 1, \dots, m$ one can write

$$y(x) = A_j e^{x z_j} + B_j e^{-x z_j}, \quad b_{j-1} < x < b_j.$$

From the equation, it follows that

$$y(b_j - 0) = y_{j+1}(b_j + 0),$$

$$\gamma_j y'_j(b_j - 0) = \gamma_{j+1} y'_{j+1}(b_j + 0).$$

Therefore the coefficients $A_1, B_1, \dots, A_m, B_m$ have to satisfy the system of equations:

$$z_1(A_1 - B_1) = w'(0); \tag{4.1}$$

for each $j = 1, \dots, m - 1$

$$A_j e^{b_j z_j} + B_j e^{-b_j z_j} = A_{j+1} e^{b_j z_{j+1}} + B_{j+1} e^{-b_j z_{j+1}}, \tag{4.2}$$

$$\gamma_j z_j (A_j e^{b_j z_j} - B_j e^{-b_j z_j}) = \gamma_{j+1} z_{j+1} (A_{j+1} e^{b_j z_{j+1}} - B_{j+1} e^{-b_j z_{j+1}});$$

$$\gamma_m z_m (A_m e^{a z_m} - B_m e^{-a z_m}) + \rho (A_m e^{a z_m} + B_m e^{-a z_m}) = 0. \tag{4.3}$$

Set

$$X_j = \begin{pmatrix} A_j e^{b_j z_j} \\ B_j e^{-b_j z_j} \end{pmatrix}, \quad K_j = \begin{pmatrix} 1 & 1 \\ \sqrt{\gamma_j} & -\sqrt{\gamma_j} \end{pmatrix}, \quad \alpha_j = \begin{pmatrix} 1 & 0 \\ 0 & e^{-2(b_{j-1} - b_j) z_j} \end{pmatrix}.$$

Then one can rewrite the equations (4.1), (4.2) and (4.3) in the matrix form:

$$\begin{pmatrix} 1 & -e^{2b_1 z_1} \end{pmatrix} X_1 = \frac{w'(0) \sqrt{\gamma_1}}{z} e^{b_1 z_1}, \tag{4.4}$$

$$e^{(b_j - b_{j+1}) z_{j+1}} K_{j+1} \alpha_{j+1} X_{j+1} = K_j X_j, \tag{4.5}$$

$$\begin{pmatrix} (\sqrt{\gamma_m} + \frac{\rho}{z}) & -(\sqrt{\gamma_m} - \frac{\rho}{z}) \end{pmatrix} X_m = 0. \tag{4.6}$$

Set

$$L(z) = (K_1^{-1} K_2 \alpha_2) \cdots (K_{m-1}^{-1} K_m \alpha_m).$$

From (4.5) we have

$$X_1 = e^{\sum_{j=1}^{m-1} (b_j - b_{j+1}) z_{j+1}} L(z) X_m.$$

Substituting this into (4.4), we obtain

$$\begin{pmatrix} 1 & -e^{2b_1 z_1} \end{pmatrix} L(z) X_m = \frac{w'(0) \sqrt{\gamma_1}}{z} e^{b_1 z_1} e^{-\sum_{j=1}^{m-1} (b_j - b_{j+1}) z_{j+1}}. \quad (4.7)$$

The equations (4.6) and (4.7) are equivalent to the equation

$$\begin{pmatrix} 1 & -\frac{\sqrt{\gamma_m} - \frac{\rho}{z}}{\sqrt{\gamma_m} + \frac{\rho}{z}} \\ \begin{pmatrix} 1 & -e^{2b_1 z_1} \end{pmatrix} L(z) \end{pmatrix} X_m = \frac{w'(0) \sqrt{\gamma_1}}{z} e^{b_1 z_1} e^{-\sum_{j=1}^{m-1} (b_j - b_{j+1}) z_{j+1}} \begin{pmatrix} 0 \\ 1 \end{pmatrix}. \quad (4.8)$$

Solving equation (4.8), we obtain X_m . The problem is the asymptotic behaviour of $L(z)$ as $\tau \longrightarrow \infty$.

Define the *transmission coefficient* T_{kl} and *reflection coefficient* R_{kl} by the formula

$$T_{kl} = \frac{2\sqrt{\gamma_k}}{\sqrt{\gamma_k} + \sqrt{\gamma_l}}, \quad R_{kl} = \frac{\sqrt{\gamma_k} - \sqrt{\gamma_l}}{\sqrt{\gamma_k} + \sqrt{\gamma_l}}.$$

Set $\delta = \min_{j=1, \dots, m} \{(b_j - b_{j-1})/\sqrt{\gamma_j}\} (> 0)$.

Lemma 4.2. *We have, as $\tau \longrightarrow \infty$*

$$L(z) = \frac{1}{T_{12} \cdots T_{m-1, m}} \begin{pmatrix} 1 & 0 \\ R_{12} & 0 \end{pmatrix} + O(e^{-2c\delta\tau}). \quad (4.9)$$

Proof. Using the expression

$$\alpha_j = \begin{pmatrix} 1 & 0 \\ 0 & 0 \end{pmatrix} + O(e^{-2c\tau(b_j - b_{j-1})/\sqrt{\gamma_j}})$$

and

$$K_j^{-1} = \frac{1}{2\sqrt{\gamma_j}} \begin{pmatrix} \sqrt{\gamma_j} & 1 \\ \sqrt{\gamma_j} & -1 \end{pmatrix},$$

we have

$$K_j \alpha_j K_j^{-1} = \frac{1}{2\sqrt{\gamma_j}} \begin{pmatrix} 1 \\ \sqrt{\gamma_j} \end{pmatrix} \begin{pmatrix} \sqrt{\gamma_j} & 1 \end{pmatrix} + O(e^{-2c\tau(b_j - b_{j-1})/\sqrt{\gamma_j}}).$$

This gives

$$\begin{aligned} & (K_2 \alpha_2 K_2^{-1}) \cdots (K_m \alpha_m K_m^{-1}) \\ &= \left(\frac{1}{2}\right)^{m-1} \frac{\prod_{j=2}^{m-1} (\sqrt{\gamma_j} + \sqrt{\gamma_{j+1}})}{\sqrt{\prod_{j=2}^m \gamma_j}} \begin{pmatrix} 1 \\ \sqrt{\gamma_2} \end{pmatrix} \begin{pmatrix} \sqrt{\gamma_m} & 1 \end{pmatrix} + O(e^{-2c\delta\tau}). \end{aligned}$$

Since

$$K_1^{-1} \begin{pmatrix} 1 \\ \sqrt{\gamma_2} \end{pmatrix} \begin{pmatrix} \sqrt{\gamma_m} & 1 \end{pmatrix} K_m = \sqrt{\frac{\gamma_m}{\gamma_1}} (\sqrt{\gamma_1} + \sqrt{\gamma_2}) \begin{pmatrix} 1 & 0 \\ \frac{\sqrt{\gamma_1} - \sqrt{\gamma_2}}{\sqrt{\gamma_1} + \sqrt{\gamma_2}} & 0 \end{pmatrix},$$

we obtain

$$L(z) = \left(\frac{1}{2}\right)^{m-1} \frac{\prod_{j=1}^{m-1} (\sqrt{\gamma_j} + \sqrt{\gamma_{j+1}})}{\sqrt{\prod_{j=1}^{m-1} \gamma_j}} \begin{pmatrix} 1 & 0 \\ \frac{\sqrt{\gamma_1} - \sqrt{\gamma_2}}{\sqrt{\gamma_1} + \sqrt{\gamma_2}} & 0 \end{pmatrix} + O(e^{-2c\delta\tau}).$$

This is nothing but (4.9).

□

As a direct consequence of (4.9) we have

$$\begin{aligned} & \begin{pmatrix} 1 & -\frac{\sqrt{\gamma_m} - \frac{\rho}{z}}{\sqrt{\gamma_m} + \frac{\rho}{z}} \end{pmatrix}^{-1} \\ & \begin{pmatrix} 1 & -e^{2b_1 z_1} \end{pmatrix} L(z) \\ &= \begin{pmatrix} 0 & T_{12} \cdots T_{m-1,m} \\ -1 & T_{12} \cdots T_{m-1,m} \end{pmatrix} + \frac{2\rho}{z \sqrt{\gamma_m}} \begin{pmatrix} 0 & 0 \\ -1 & T_{12} \cdots T_{m-1,m} \end{pmatrix} + O\left(\frac{1}{\tau^2}\right) \end{aligned}$$

and (4.8) therefore yields

$$X_m = \frac{w'(0) \sqrt{\gamma_1}}{z} e^{b_1 z_1} e^{-\sum_{j=1}^{m-1} (b_j - b_{j+1}) z_{j+1}} T_{12} \cdots T_{m-1,m} \left\{ \begin{pmatrix} 1 \\ 1 + \frac{2\rho}{z \sqrt{\gamma_m}} \end{pmatrix} + O\left(\frac{1}{\tau^2}\right) \right\}$$

as $\tau \longrightarrow \infty$.

Define

$$\varphi_j = \sum_{l=1}^{j-1} b_l (z_l - z_{l+1}), \quad j = 2, \dots, m$$

and

$$\varphi(x) = \begin{cases} x z_1, & \text{if } -\infty < x < b_1, \\ x z_2 + \varphi_2, & \text{if } b_1 < x < b_2, \\ \vdots & \\ x z_m + \varphi_m, & \text{if } b_{m-1} < x < \infty. \end{cases}$$

The function φ has the unique continuous extension to the whole real line since $\varphi(b_j - 0) = \varphi(b_j + 0)$ for each $j = 1, \dots, m - 1$. We denote the extension by φ again.

Since $y(a) = (X_m)_1 + (X_m)_2$, $a = b_m$ and

$$\begin{aligned} & b_1 z_1 - \sum_{j=1}^{m-1} (b_j - b_{j+1}) z_{j+1} \\ &= b_1 z_1 - (b_1 - b_2) z_2 - (b_2 - b_3) z_3 - \dots - (b_{m-1} - b_m) z_m \\ &= b_1(z_1 - z_2) + b_2(z_2 - z_3) + \dots + b_{m-1}(z_{m-1} - z_m) + b_m z_m = \varphi(b_m), \end{aligned}$$

we obtain the formula

$$y(a) = \frac{2w'(0)\sqrt{\gamma_1}}{z} e^{\varphi(a)} T_{12} \dots T_{m-1,m} \left\{ 1 + \frac{\rho}{z\sqrt{\gamma_m}} + O\left(\frac{1}{\tau^2}\right) \right\}. \quad (4.10)$$

Note that

$$\varphi(a) = -z \left(\frac{b_1}{\sqrt{\gamma_1}} + \sum_{j=1}^{m-1} \frac{b_{j+1} - b_j}{\sqrt{\gamma_{j+1}}} \right). \quad (4.11)$$

5 Proof of Theorem 2.3. Part 2. Asymptotic behaviour of $\Psi(a)$

Integration by parts yields that the function Ψ is the (weak) solution of the equation $(\tilde{\gamma} y')' - z^2 y = 0$ in $\mathbf{R}$ if and only if Ψ satisfies, for each $j = 1, \dots, m - 1$

$$\Psi(b_j - 0) = \Psi(b_j + 0),$$

$$\gamma_j \Psi'(b_j - 0) = \gamma_{j+1} \Psi'(b_j + 0).$$

This yields the system of equations for $B_1, A_2, B_2, \dots, B_{m-1}, A_m$:

$$e^{(b_j - b_{j+1}) z_{j+1}} K_{j+1} \alpha_{j+1} Y_{j+1} = K_j Y_j, \quad j = 1, \dots, m - 1 \quad (5.1)$$

where

$$Y_1 = \begin{pmatrix} e^{b_1 z_1} \\ B_1 e^{-b_1 z_1} \end{pmatrix}, \quad Y_j = \begin{pmatrix} A_j e^{b_j z_j} \\ B_j e^{-b_j z_j} \end{pmatrix}, \quad Y_m = A_m e^{b_m z_m} \begin{pmatrix} 1 \\ 0 \end{pmatrix}.$$

From (5.2) one has

$$\begin{aligned}
Y_1 &= e^{\sum_{j=1}^{m-1} (b_j - b_{j+1}) z_{j+1}} L(z) Y_m \\
&= A_m e^{b_m z_m} e^{\sum_{j=1}^{m-1} (b_j - b_{j+1}) z_{j+1}} L(z) \begin{pmatrix} 1 \\ 0 \end{pmatrix}.
\end{aligned} \tag{5.3}$$

Set $\delta = \min_{j=1, \dots, m} \{(b_j - b_{j-1})/\sqrt{\gamma_j}\} (> 0)$.

The following indicates the meaning of the coefficients T_{kl} and R_{kl} .

Lemma 5.1. *For sufficiently large τ the system of equations (5.1) is uniquely solvable and, as $\tau \rightarrow \infty$ the formulae*

$$A_j e^{-b_1 z_1} e^{b_j z_j} e^{\sum_{l=1}^{j-1} (b_l - b_{l+1}) z_{l+1}} = T_{12} \cdots T_{j-1,j} + O(e^{-2c\delta\tau}) \tag{5.4}$$

and

$$B_j e^{-b_1 z_1} e^{-b_j z_j} e^{\sum_{l=1}^{j-1} (b_l - b_{l+1}) z_{l+1}} = R_{j,j+1} T_{12} \cdots T_{j-1,j} + O(e^{-2c\delta\tau}), \tag{5.5}$$

are valid.

Proof. Using (4.9) and (5.3), we find A_m for a sufficient large τ and obtain (5.4) for $j = m$. Next (5.1) for $j = m - 1$ yields that A_{m-1} and B_{m-1} are uniquely determined and that the formulae (5.4) and (5.5) for $j = m - 1$. For general j we make use of the recurrence formulae

$$\begin{aligned}
A_j &= \frac{1}{T_{j,j+1}} A_{j+1} e^{b_j (z_{j+1} - z_j)} + \frac{R_{j,j+1}}{T_{j,j+1}} B_{j+1} e^{-b_j (z_{j+1} + z_j)}, \\
B_j &= \frac{R_{j,j+1}}{T_{j,j+1}} A_{j+1} e^{b_j (z_{j+1} + z_j)} + \frac{1}{T_{j,j+1}} B_{j+1} e^{-b_j (z_{j+1} - z_j)},
\end{aligned}$$

which are equivalent to (5.1). Note that we set $A_1 = 1$ and $B_m = 0$.

□

From Lemma 5.1 one has, as $\tau \longrightarrow \infty$

$$A_2 e^{-\varphi_2} = T_{12} + O(e^{-2c\delta\tau}),$$

$$A_3 e^{-\varphi_3} = T_{12} T_{23} + O(e^{-2c\delta\tau}),$$

$$\vdots$$

$$A_m e^{-\varphi_m} = T_{12} T_{23} \cdots T_{m-1,m} + O(e^{-2c\delta\tau});$$

$$B_1 e^{-2b_1 z_1} = R_{12} + O(e^{-2c\delta\tau}),$$

$$B_2 e^{-2b_2 z_2} e^{-\varphi_2} = T_{12} R_{23} + O(e^{-2c\delta\tau}),$$

$$\vdots$$

$$B_{m-1} e^{-2b_{m-1} z_{m-1}} e^{-\varphi_{m-1}} = T_{12} T_{23} \cdots T_{m-2,m-1} R_{m-1,m} + O(e^{-2c\delta\tau}).$$

Moreover, it follows that

$$\frac{B_j e^{-x z_j}}{A_j e^{x z_j}} = O(e^{-2c\tau(b_j-x)/\sqrt{\gamma_j}}), \quad x < b_j.$$

This gives, as $\tau \longrightarrow \infty$ the asymptotic formula of Ψ :

$$\Psi(x) \sim \begin{cases} e^{\varphi(x)}, & \text{if } -\infty < x < b_1, \\ T_{12} e^{\varphi(x)}, & \text{if } b_1 < x < b_2, \\ \vdots \\ T_{12} \cdots T_{m-1,m} e^{\varphi(x)}, & \text{if } b_{m-1} < x < \infty. \end{cases}$$

The formula (5.4) for $j = m$ gives

$$\Psi(a) e^{-\varphi(a)} = T_{12} \cdots T_{m-1,m} + O(e^{-2c\delta\tau}). \quad (5.6)$$

The following estimates are a direct corollary of (5.4) and (5.5):

$$|A_j| = O \left(e^{-c b_1 \tau / \sqrt{\gamma_1}} e^{c b_j \tau / \sqrt{\gamma_j}} e^{-c \sum_{l=1}^{j-1} (b_{l+1} - b_l) \tau / \sqrt{\gamma_{l+1}}} \right);$$

$$|B_j| = O \left(e^{-c b_1 \tau / \sqrt{\gamma_1}} e^{-c b_j \tau / \sqrt{\gamma_j}} e^{-c \sum_{l=1}^{j-1} (b_{l+1} - b_l) \tau / \sqrt{\gamma_{l+1}}} \right).$$

Applying these estimates to the expression

$$\int_{b_{j-1}}^{b_j} u(\xi, T) \Psi(\xi) d\xi = A_j \int_{b_{j-1}}^{b_j} u(\xi, T) e^{\xi z_j} d\xi + B_j \int_{b_{j-1}}^{b_j} u(\xi, T) e^{-\xi z_j} d\xi,$$

we obtain the estimate

$$\int_0^a u(\xi, T) \Psi(\xi) d\xi = O(1). \quad (5.7)$$

Recalling the definition of w , the equation $\Psi'(a) = z_m \Psi(a)$ and using integration by parts we have

$$\begin{aligned} I_c(\tau) &= \gamma_1 w'(0) \Psi(0) - w(0) \gamma_1 \Psi'(0) \\ &= -(\rho + \gamma_m z_m) \Psi(a) w(a) - e^{-z^2 T} \int_0^a u(\xi, T) \Psi(\xi) d\xi. \end{aligned}$$

Then Lemma 4.1, (4.10), (5.6) and (5.7) yield the asymptotic formula for the indicator function.

Proposition 5.2. *As $\tau \longrightarrow \infty$ the formula*

$$\begin{aligned} I_c(\tau) e^{-2\varphi(a)} &= -2 \sqrt{\gamma_1 \gamma_m} w'(0) (T_{12} \cdots T_{m-1, m})^2 \left\{ 1 + \frac{2\rho}{z \sqrt{\gamma_m}} + O\left(\frac{1}{\tau^2}\right) \right\} \\ &\quad - \tau \left\{ T - 2c \left(\frac{b_1}{\sqrt{\gamma_1}} + \sum_{j=1}^{m-1} \frac{b_{j+1} - b_j}{\sqrt{\gamma_{j+1}}} \right) \right\} \\ &\quad + O(\tau e^{-\tau}), \end{aligned}$$

is valid.

Theorem 2.3 is an immediate corollary of (4.11), Proposition 5.2, the expression

$$w'(0) = \int_0^T e^{-z^2 t} u_x(0, t) dt,$$

the assumption (2.7) and the fact $w'(0) = O(1)$ as $\tau \longrightarrow \infty$.

Remark 5.1. Once $\varphi(a)$ is known (see (4.11)), then one immediately obtains the extraction formula of ρ :

$$\lim_{\tau \longrightarrow \infty} \left(\frac{I_c(\tau) e^{-2\varphi(a)}}{2 \sqrt{\gamma_1 \gamma_m} w'(0) (T_{12} \cdots T_{m-1, m})^2} + 1 \right) z \sqrt{\gamma_m} = -2\rho.$$

6 Proof of Theorem 2.5

Define

$$w(x, \tau) = \int_0^T e^{-z^2 t} u(x, t) dt, \quad 0 < x < a.$$

This w satisfies

$$(\gamma w')' - z^2 w = e^{-z^2 T} u(x, T), \quad \text{in }]0, a[,$$

$$\gamma(a) w'(a) + \rho w(a) = 0.$$

Integration by parts gives the expression

$$I(z) = -w(a, z)(\gamma(a) \Psi'(a; z, M) + \rho \Psi(a; z, M)) - \int_0^a e^{-z^2 T} u(x, T) \Psi(x; z, M) dx. \quad (6.1)$$

Proposition 2.4 gives

$$\gamma(a) \Psi'(a; z, M) + \rho \Psi(a; z, M) = \frac{z}{\gamma(a)^{3/4}} e^{K_a z \pi} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\}. \quad (6.2)$$

Therefore it suffices to study the asymptotic behaviour of $w(a, z)$ as $|z| \rightarrow \infty$. For the purpose first we study the asymptotic behaviour of the unique solution of the boundary value problem as $|z| \rightarrow \infty$:

$$(\gamma y')' - z^2 y = 0 \text{ in }]0, a[,$$

$$y'(0) = 1,$$

$$\gamma(a) y'(a) + \rho y(a) = 0.$$

We make use of the Liouville transform. Define

$$K_a = \frac{1}{\pi} \int_0^a \frac{dx}{\sqrt{\gamma(x)}}$$

and

$$s(x; a) = \frac{1}{K_a} \int_0^x \frac{dx}{\sqrt{\gamma(x)}}, \quad 0 \leq x \leq a.$$

Denote by $x(s; a)$, $0 \leq s \leq \pi$ the inverse of the function $s = s(x; a)$. Set

$$\tilde{y}(s) = K_a \gamma(0)^{1/4} \gamma(x(s; a))^{1/4} y(x(s; a)). \quad (6.3)$$

Then this $\tilde{y}$ satisfies

$$\tilde{y}'' - (K_a^2 z^2 + g_a(s)) \tilde{y} = 0 \text{ in }]0, \pi[,$$

$$\tilde{y}'(0) - h_a \tilde{y}(0) = 1,$$

$$\tilde{y}'(\pi) + H_a \tilde{y}(\pi) = 0$$

where

$$h_a = \frac{\gamma'(0)}{4K_a \gamma(0)^{3/2}}, \quad H_a = \frac{4\rho - \gamma'(a)}{4K_a \gamma(a)^{3/2}}.$$

and

$$f_a(s) = \gamma(x(s; a))^{1/4}, \quad g_a(s) = \frac{f_a''(s)}{f_a(s)}.$$

Lemma 6.1. *As $|z| \rightarrow \infty$ we have*

$$\tilde{y}(\pi) = \frac{2}{K_a z} e^{K_a z \pi} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\}. \quad (6.4)$$

Proof. It is easy to see that $\tilde{y}$ has the expression

$$\tilde{y}(s) = \frac{\varphi(s)}{\varphi'(0) - h_a \varphi(0)}$$

where φ is the unique solution of the initial value problem:

$$\varphi'' - (K_a^2 z^2 + g(s))\varphi = 0 \text{ in }]0, \pi[,$$

$$\varphi(\pi) = 1,$$

$$\varphi'(\pi) = -H_a.$$

Here we cite a known important fact: there exists a fundamental system of solutions $e_1(x, z)$ and $e_2(x, z)$ of equation $y'' - (K_a^2 z^2 + g_a(s))y = 0$ in $]0, \pi[$ such that as $|z| \rightarrow \infty$, $\operatorname{Re} z \leq 0$, uniformly in x ,

$$e_1(s, z) = e^{K_a z s} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\},$$

$$e_1'(s, z) = K_a z e^{K_a z s} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\},$$

$$e_2(s, z) = e^{-K_a z s} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\},$$

$$e_2'(s, z) = -K_a z e^{-K_a z s} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\}$$

See again Theorem 1 of p. 48 in [16].

Thus one can write

$$\varphi(s) = A_1 e_1(s, z) + A_2 e_2(s, z)$$

where A_1 and A_2 are constants. The initial conditions on φ yields

$$A_1 = \frac{1}{W(e_1(\cdot, z), e_2(\cdot, z))(\pi)} (e_2'(\pi, z) + e_2(\pi, z)H_a),$$

$$A_2 = -\frac{1}{W(e_1(\cdot, z), e_2(\cdot, z))(\pi)} (e_1'(\pi, z) + e_1(\pi, z)H_a).$$

The asymptotic behaviour of e_1 and e_2 yields

$$W(e_1(\cdot, z), e_2(\cdot, z))(\pi) = -2K_a z \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\}$$

and also

$$A_1 = \frac{1}{2} e^{-K_a z \pi} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\}, \quad A_2 = \frac{1}{2} e^{K_a z \pi} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\}.$$

From these we obtain

$$\varphi'(0) - h_a \varphi(0) = \frac{K_a z}{2} e^{-K_a z \pi} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\},$$

$$\varphi(\pi) = 1 + O\left(\frac{1}{|z|}\right).$$

This yields (6.4).

□

A combination of (6.3) and (6.4) gives

$$y(a) = \frac{2 e^{K_a z \pi}}{K_a^2 \gamma(0)^{1/4} \gamma(a)^{1/4} z} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\}. \quad (6.5)$$

Using a standard argument, we have

$$\frac{w(x, z)}{w'(0, z)} = y(x) + O(e^{-\operatorname{Re} z^2 T}). \quad (6.6)$$

A combination of (6.5) and (6.6) yields

$$w(a, z) = \frac{2 w'(0, z)}{K_a^2 \gamma(0)^{1/4} \gamma(a)^{1/4}} \frac{e^{K_a z \pi}}{z} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\} + O(e^{-\operatorname{Re} z^2 T} w'(0, z)). \quad (6.7)$$

Now from (6.1), (6.2) and (6.7) we obtain the crucial formula:

$$\begin{aligned} I(z) &= -\frac{2 w'(0, z)}{K_a^2 \gamma(0)^{1/4}} e^{2 K_a z \pi} \left\{ 1 + O\left(\frac{1}{|z|}\right) \right\} \\ &+ O\left(e^{-\operatorname{Re} z^2 T} |w'(0, z)| |z| e^{K_a \operatorname{Re} z \pi}\right) + O\left(e^{-\operatorname{Re} z^2 T}\right). \end{aligned} \quad (6.8)$$

Then Theorem 2.5 follows from this formula (6.8), for the choices $z = -c\tau(1+i\sqrt{1-1/c^2\tau})$ (case (a)) and $z = -\tau$ (case (b)) and the expression

$$w'(0, z) = \int_0^T e^{-z^2 t} u_x(0, t) dt.$$

More precisely, both (2.11) in case (a) and (2.13) in case (b) ensure

$$C\tau^\mu \leq |w'(0, z)|, \quad \tau \geq \tau^0.$$

From Remark 1.1 one has $w'(0, z) = O(1)$ as $\tau \rightarrow \infty$. These yields the estimate: for suitable positive constants C_1, C_2 and for all $\tau \gg 1$

$$C_1 \tau^\mu \leq |I(z)| e^{-2 K_a \operatorname{Re} z \pi} \leq C_2.$$

Note that (2.10) is essential in the case (a). This completes the proof of Theorem 2.5.

Acknowledgement

This research was partially supported by Grant-in-Aid for Scientific Research (C)(No. 18540160) of Japan Society for the Promotion of Science.

References

- [1] Bryan, K. and Caudill, F. Jr., Uniqueness for a boundary identification problem in thermal imaging, *Differential Equations and Computational Simulations III*, *Electric Journal of Differential Equations*, Conference 01, 1997, 23-39.
- [2] Canuto, B., Rosset, E. and Vessella, S., Quantitative estimate of unique continuation for parabolic equations and inverse initial-boundary value problems with unknown boundaries, *Trans. Amer. Math. Soc.*, 354(2002), 491-535.
- [3] Dautray, R. and Lions J.-L., *Mathematical Analysis and Numerical Methods for Science and Technology*, 5, *Evolution Problems I*, Springer, Berlin, 1992.
- [4] Friedman, A. and Isakov, V., On the uniqueness in the inverse conductivity problem with one measurement, *Indiana Univ. Math. J.*, 38(1989), 563-579.
- [5] Ikehata, M., Reconstruction of the shape of the inclusion by boundary measurements, *Comm. PDE.*, 23(1998), 1459-1474.
- [6] Ikehata, M., Enclosing a polygonal cavity in a two-dimensional bounded domain from Cauchy data, *Inverse Problems*, 15(1999), 1231-1241.
- [7] Ikehata, M., Reconstruction of the support function for inclusion from boundary measurements, *J. Inverse Ill-Posed Probl.*, 8(2000), 367-378.
- [8] Ikehata, M., On reconstruction in the inverse conductivity problem with one measurement, *Inverse Problems*, 16(2000), 785-793.
- [9] Ikehata, M., Exponentially growing solutions, multilayered anisotropic material and the enclosure method, *Inverse Problems*, 19(2003), 1065-1079.
- [10] Ikehata, M., A new formulation of the probe method and related problems, *Inverse Problems*, 21(2005), 413-426.
- [11] Ikehata, M., Travel time and heat equation. One space dimensional case, submitted, 2006.
- [12] Ikehata, M. and Ohe, T., Numerical method for finding the convex hull of polygonal cavities using enclosure method, *Inverse Problems*, 18(2002), 111-124.
- [13] Ikehata, M. and Ohe, T., A numerical method for finding the convex hull of inclusions using the enclosure method, *Electromagnetic Nondestructive Evaluation (VI)* (*Studies in Applied Electromagnetics and Mechanics*, Vol. 23), F. Kojima et al. (Eds), IOS Press, Amsterdam, 2002, 21-28.
- [14] Kirsch, A., Characterization of the shape of a scattering obstacle using the spectral data of the far field operator, *Inverse Problems*, 14(1998), 1489-1512.
- [15] Kirsch, A., New characterizations of solutions in inverse scattering theory, *Appl. Anal.*, 76(2000), 319-350.

- [16] Naimark, M. A., Linear Differential Operators parts I, New York, Ungar, Engl. Transl., 1967.

e-mail address

ikehata@math.sci.gunma-u.ac.jp